

Fuse Voltage Drop Chart -JCase Cartridge Style

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Blue | Pink | Green | Red | Yellow | Black | Blue |
|-------------------|---------------------|---------------------|---------------------|---------------------|---------------------|---------------------|----------------------|
| Measurement mV | Cartridge 20 Amp | Cartridge 30 Amp | Cartridge 40 Amp | Cartridge 50 Amp | Cartridge 60 Amp | Cartridge 80 Amp | Cartridge 100 Amp |
| 0.1 | 17 | 19 | 26 | 42 | 59 | 81 | 213 |
| 0.2 | 33 | 38 | 53 | 83 | 118 | 163 | 426 |
| 0.3 | 50 | 58 | 79 | 125 | 176 | 244 | 638 |
| 0.4 | 67 | 77 | 105 | 167 | 235 | 325 | 851 |
| 0.5 | 83 | 96 | 132 | 208 | 294 | 407 | 1064 |
| 0.6 | 100 | 115 | 158 | 250 | 353 | 488 | 1277 |
| 0.7 | 117 | 135 | 184 | 292 | 412 | 569 | 1489 |
| 0.8 | 133 | 154 | 211 | 333 | 471 | 650 | 1702 |
| 0.9 | 150 | 173 | 237 | 375 | 529 | 732 | 1915 |
| 1 | 167 | 192 | 263 | 417 | 588 | 813 | 2128 |
| 1.1 | 183 | 212 | 289 | 458 | 647 | 894 | 2340 |
| 1.2 | 200 | 231 | 316 | 500 | 706 | 976 | 2553 |
| 1.3 | 217 | 250 | 342 | 542 | 765 | 1057 | 2766 |
| 1.4 | 233 | 269 | 368 | 583 | 824 | 1138 | 2979 |
| 1.5 | 250 | 288 | 395 | 625 | 882 | 1220 | 3191 |
| 1.6 | 267 | 308 | 421 | 667 | 941 | 1301 | 3404 |
| 1.7 | 283 | 327 | 447 | 708 | 1000 | 1382 | 3617 |
| 1.8 | 300 | 346 | 474 | 750 | 1059 | 1463 | 3830 |
| 1.9 | 317 | 365 | 500 | 792 | 1118 | 1545 | 4043 |
| 2 | 333 | 385 | 526 | 833 | 1176 | 1626 | 4255 |
| 2.1 | 350 | 404 | 553 | 875 | 1235 | 1707 | 4468 |
| 2.2 | 367 | 423 | 579 | 917 | 1294 | 1789 | 4681 |
| 2.3 | 383 | 442 | 605 | 958 | 1353 | 1870 | 4894 |
| 2.4 | 400 | 462 | 632 | 1000 | 1412 | 1951 | 5106 |
| 2.5 | 417 | 481 | 658 | 1042 | 1471 | 2033 | 5319 |
| 2.6 | 433 | 500 | 684 | 1083 | 1529 | 2114 | 5532 |
| 2.7 | 450 | 519 | 711 | 1125 | 1588 | 2195 | 5745 |
| 2.8 | 467 | 538 | 737 | 1167 | 1647 | 2276 | 5957 |
| 2.9 | 483 | 558 | 763 | 1208 | 1706 | 2358 | 6170 |
| 3 | 500 | 577 | 789 | 1250 | 1765 | 2439 | 6383 |
| 3.1 | 517 | 596 | 816 | 1292 | 1824 | 2520 | 6596 |
| 3.2 | 533 | 615 | 842 | 1333 | 1882 | 2602 | 6809 |
| 3.3 | 550 | 635 | 868 | 1375 | 1941 | 2683 | 7021 |
| 3.4 | 567 | 654 | 895 | 1417 | 2000 | 2764 | 7234 |
| 3.5 | 583 | 673 | 921 | 1458 | 2059 | 2846 | 7447 |
| 3.6 | 600 | 692 | 947 | 1500 | 2118 | 2927 | 7660 |
| 3.7 | 617 | 712 | 974 | 1542 | 2176 | 3008 | 7872 |
| 3.8 | 633 | 731 | 1000 | 1583 | 2235 | 3089 | 8085 |
| 3.9 | 650 | 750 | 1026 | 1625 | 2294 | 3171 | 8298 |
| 4 | 667 | 769 | 1053 | 1667 | 2353 | 3252 | 8511 |
| 4.1 | 683 | 788 | 1079 | 1708 | 2412 | 3333 | 8723 |
| 4.2 | 700 | 808 | 1105 | 1750 | 2471 | 3415 | 8936 |
| 4.3 | 717 | 827 | 1132 | 1792 | 2529 | 3496 | 9149 |
| 4.4 | 733 | 846 | 1158 | 1833 | 2588 | 3577 | 9362 |
| 4.5 | 750 | 865 | 1184 | 1875 | 2647 | 3659 | 9574 |
| 4.6 | 767 | 885 | 1211 | 1917 | 2706 | 3740 | 9787 |
| 4.7 | 783 | 904 | 1237 | 1958 | 2765 | 3821 | 10000 |
| 4.8 | 800 | 923 | 1263 | 2000 | 2824 | 3902 | 10213 |
| 4.9 | 817 | 942 | 1289 | 2042 | 2882 | 3984 | 10426 |
| 5 | 833 | 962 | 1316 | 2083 | 2941 | 4065 | 10638 |

Fuse Voltage Drop Chart -JCase Cartridge Style

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Blue | Pink | Green | Red | Yellow | Black | Blue |
|-------------------|---------------------|---------------------|---------------------|---------------------|---------------------|---------------------|----------------------|
| Measurement mV | Cartridge 20 Amp | Cartridge 30 Amp | Cartridge 40 Amp | Cartridge 50 Amp | Cartridge 60 Amp | Cartridge 80 Amp | Cartridge 100 Amp |
| 5.1 | 850 | 981 | 1342 | 2125 | 3000 | 4146 | 10851 |
| 5.2 | 867 | 1000 | 1368 | 2167 | 3059 | 4228 | 11064 |
| 5.3 | 883 | 1019 | 1395 | 2208 | 3118 | 4309 | 11277 |
| 5.4 | 900 | 1038 | 1421 | 2250 | 3176 | 4390 | 11489 |
| 5.5 | 917 | 1058 | 1447 | 2292 | 3235 | 4472 | 11702 |
| 5.6 | 933 | 1077 | 1474 | 2333 | 3294 | 4553 | 11915 |
| 5.7 | 950 | 1096 | 1500 | 2375 | 3353 | 4634 | 12128 |
| 5.8 | 967 | 1115 | 1526 | 2417 | 3412 | 4715 | 12340 |
| 5.9 | 983 | 1135 | 1553 | 2458 | 3471 | 4797 | 12553 |
| 6 | 1000 | 1154 | 1579 | 2500 | 3529 | 4878 | 12766 |
| 6.1 | 1017 | 1173 | 1605 | 2542 | 3588 | 4959 | 12979 |
| 6.2 | 1033 | 1192 | 1632 | 2583 | 3647 | 5041 | 13191 |
| 6.3 | 1050 | 1212 | 1658 | 2625 | 3706 | 5122 | 13404 |
| 6.4 | 1067 | 1231 | 1684 | 2667 | 3765 | 5203 | 13617 |
| 6.5 | 1083 | 1250 | 1711 | 2708 | 3824 | 5285 | 13830 |
| 6.6 | 1100 | 1269 | 1737 | 2750 | 3882 | 5366 | 14043 |
| 6.7 | 1117 | 1288 | 1763 | 2792 | 3941 | 5447 | 14255 |
| 6.8 | 1133 | 1308 | 1789 | 2833 | 4000 | 5528 | 14468 |
| 6.9 | 1150 | 1327 | 1816 | 2875 | 4059 | 5610 | 14681 |
| 7 | 1167 | 1346 | 1842 | 2917 | 4118 | 5691 | 14894 |
| 7.1 | 1183 | 1365 | 1868 | 2958 | 4176 | 5772 | 15106 |
| 7.2 | 1200 | 1385 | 1895 | 3000 | 4235 | 5854 | 15319 |
| 7.3 | 1217 | 1404 | 1921 | 3042 | 4294 | 5935 | 15532 |
| 7.4 | 1233 | 1423 | 1947 | 3083 | 4353 | 6016 | 15745 |
| 7.5 | 1250 | 1442 | 1974 | 3125 | 4412 | 6098 | 15957 |
| 7.6 | 1267 | 1462 | 2000 | 3167 | 4471 | 6179 | 16170 |
| 7.7 | 1283 | 1481 | 2026 | 3208 | 4529 | 6260 | 16383 |
| 7.8 | 1300 | 1500 | 2053 | 3250 | 4588 | 6341 | 16596 |
| 7.9 | 1317 | 1519 | 2079 | 3292 | 4647 | 6423 | 16809 |
| 8 | 1333 | 1538 | 2105 | 3333 | 4706 | 6504 | 17021 |
| 8.1 | 1350 | 1558 | 2132 | 3375 | 4765 | 6585 | 17234 |
| 8.2 | 1367 | 1577 | 2158 | 3417 | 4824 | 6667 | 17447 |
| 8.3 | 1383 | 1596 | 2184 | 3458 | 4882 | 6748 | 17660 |
| 8.4 | 1400 | 1615 | 2211 | 3500 | 4941 | 6829 | 17872 |
| 8.5 | 1417 | 1635 | 2237 | 3542 | 5000 | 6911 | 18085 |
| 8.6 | 1433 | 1654 | 2263 | 3583 | 5059 | 6992 | 18298 |
| 8.7 | 1450 | 1673 | 2289 | 3625 | 5118 | 7073 | 18511 |
| 8.8 | 1467 | 1692 | 2316 | 3667 | 5176 | 7154 | 18723 |
| 8.9 | 1483 | 1712 | 2342 | 3708 | 5235 | 7236 | 18936 |
| 9 | 1500 | 1731 | 2368 | 3750 | 5294 | 7317 | 19149 |
| 9.1 | 1517 | 1750 | 2395 | 3792 | 5353 | 7398 | 19362 |
| 9.2 | 1533 | 1769 | 2421 | 3833 | 5412 | 7480 | 19574 |
| 9.3 | 1550 | 1788 | 2447 | 3875 | 5471 | 7561 | 19787 |
| 9.4 | 1567 | 1808 | 2474 | 3917 | 5529 | 7642 | 20000 |
| 9.5 | 1583 | 1827 | 2500 | 3958 | 5588 | 7724 | 20213 |
| 9.6 | 1600 | 1846 | 2526 | 4000 | 5647 | 7805 | 20426 |
| 9.7 | 1617 | 1865 | 2553 | 4042 | 5706 | 7886 | 20638 |
| 9.8 | 1633 | 1885 | 2579 | 4083 | 5765 | 7967 | 20851 |
| 9.9 | 1650 | 1904 | 2605 | 4125 | 5824 | 8049 | 21064 |
| 10 | 1667 | 1923 | 2632 | 4167 | 5882 | 8130 | 21277 |

Fuse Voltage Drop Chart - Maxi Fuse


Circuit Current Across Fuse (milliAmps)



| Fuse Color | Yellow | Grey | Green | Blu-Green | Orange | Red | Blue | Tan | Clear |
|-------------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|
| Measurement mV | Maxi 20 Amp | Maxi 25 Amp | Maxi 30 Amp | Maxi 35 Amp | Maxi 40 Amp | Maxi 50 Amp | Maxi 60 Amp | Maxi 70 Amp | Maxi 80 Amp |
| 0.1 | 32 | 42 | 51 | 58 | 70 | 91 | 112 | 156 | 185 |
| 0.2 | 65 | 84 | 103 | 117 | 141 | 182 | 225 | 313 | 370 |
| 0.3 | 97 | 126 | 154 | 175 | 211 | 273 | 337 | 469 | 556 |
| 0.4 | 129 | 167 | 205 | 234 | 282 | 364 | 449 | 625 | 741 |
| 0.5 | 161 | 209 | 256 | 292 | 352 | 455 | 562 | 781 | 926 |
| 0.6 | 194 | 251 | 308 | 351 | 423 | 545 | 674 | 938 | 1111 |
| 0.7 | 226 | 293 | 359 | 409 | 493 | 636 | 787 | 1094 | 1296 |
| 0.8 | 258 | 335 | 410 | 468 | 563 | 727 | 899 | 1250 | 1481 |
| 0.9 | 290 | 377 | 462 | 526 | 634 | 818 | 1011 | 1406 | 1667 |
| 1 | 323 | 418 | 513 | 585 | 704 | 909 | 1124 | 1563 | 1852 |
| 1.1 | 355 | 460 | 564 | 643 | 775 | 1000 | 1236 | 1719 | 2037 |
| 1.2 | 387 | 502 | 615 | 702 | 845 | 1091 | 1348 | 1875 | 2222 |
| 1.3 | 419 | 544 | 667 | 760 | 915 | 1182 | 1461 | 2031 | 2407 |
| 1.4 | 452 | 586 | 718 | 819 | 986 | 1273 | 1573 | 2188 | 2593 |
| 1.5 | 484 | 628 | 769 | 877 | 1056 | 1364 | 1685 | 2344 | 2778 |
| 1.6 | 516 | 669 | 821 | 936 | 1127 | 1455 | 1798 | 2500 | 2963 |
| 1.7 | 548 | 711 | 872 | 994 | 1197 | 1545 | 1910 | 2656 | 3148 |
| 1.8 | 581 | 753 | 923 | 1053 | 1268 | 1636 | 2022 | 2813 | 3333 |
| 1.9 | 613 | 795 | 974 | 1111 | 1338 | 1727 | 2135 | 2969 | 3519 |
| 2 | 645 | 837 | 1026 | 1170 | 1408 | 1818 | 2247 | 3125 | 3704 |
| 2.1 | 677 | 879 | 1077 | 1228 | 1479 | 1909 | 2360 | 3281 | 3889 |
| 2.2 | 710 | 921 | 1128 | 1287 | 1549 | 2000 | 2472 | 3438 | 4074 |
| 2.3 | 742 | 962 | 1179 | 1345 | 1620 | 2091 | 2584 | 3594 | 4259 |
| 2.4 | 774 | 1004 | 1231 | 1404 | 1690 | 2182 | 2697 | 3750 | 4444 |
| 2.5 | 806 | 1046 | 1282 | 1462 | 1761 | 2273 | 2809 | 3906 | 4630 |
| 2.6 | 839 | 1088 | 1333 | 1520 | 1831 | 2364 | 2921 | 4063 | 4815 |
| 2.7 | 871 | 1130 | 1385 | 1579 | 1901 | 2455 | 3034 | 4219 | 5000 |
| 2.8 | 903 | 1172 | 1436 | 1637 | 1972 | 2545 | 3146 | 4375 | 5185 |
| 2.9 | 935 | 1213 | 1487 | 1696 | 2042 | 2636 | 3258 | 4531 | 5370 |
| 3 | 968 | 1255 | 1538 | 1754 | 2113 | 2727 | 3371 | 4688 | 5556 |
| 3.1 | 1000 | 1297 | 1590 | 1813 | 2183 | 2818 | 3483 | 4844 | 5741 |
| 3.2 | 1032 | 1339 | 1641 | 1871 | 2254 | 2909 | 3596 | 5000 | 5926 |
| 3.3 | 1065 | 1381 | 1692 | 1930 | 2324 | 3000 | 3708 | 5156 | 6111 |
| 3.4 | 1097 | 1423 | 1744 | 1988 | 2394 | 3091 | 3820 | 5313 | 6296 |
| 3.5 | 1129 | 1464 | 1795 | 2047 | 2465 | 3182 | 3933 | 5469 | 6481 |
| 3.6 | 1161 | 1506 | 1846 | 2105 | 2535 | 3273 | 4045 | 5625 | 6667 |
| 3.7 | 1194 | 1548 | 1897 | 2164 | 2606 | 3364 | 4157 | 5781 | 6852 |
| 3.8 | 1226 | 1590 | 1949 | 2222 | 2676 | 3455 | 4270 | 5938 | 7037 |
| 3.9 | 1258 | 1632 | 2000 | 2281 | 2746 | 3545 | 4382 | 6094 | 7222 |
| 4 | 1290 | 1674 | 2051 | 2339 | 2817 | 3636 | 4494 | 6250 | 7407 |
| 4.1 | 1323 | 1715 | 2103 | 2398 | 2887 | 3727 | 4607 | 6406 | 7593 |
| 4.2 | 1355 | 1757 | 2154 | 2456 | 2958 | 3818 | 4719 | 6563 | 7778 |
| 4.3 | 1387 | 1799 | 2205 | 2515 | 3028 | 3909 | 4831 | 6719 | 7963 |
| 4.4 | 1419 | 1841 | 2256 | 2573 | 3099 | 4000 | 4944 | 6875 | 8148 |
| 4.5 | 1452 | 1883 | 2308 | 2632 | 3169 | 4091 | 5056 | 7031 | 8333 |
| 4.6 | 1484 | 1925 | 2359 | 2690 | 3239 | 4182 | 5169 | 7188 | 8519 |
| 4.7 | 1516 | 1967 | 2410 | 2749 | 3310 | 4273 | 5281 | 7344 | 8704 |
| 4.8 | 1548 | 2008 | 2462 | 2807 | 3380 | 4364 | 5393 | 7500 | 8889 |
| 4.9 | 1581 | 2050 | 2513 | 2865 | 3451 | 4455 | 5506 | 7656 | 9074 |
| 5 | 1613 | 2092 | 2564 | 2924 | 3521 | 4545 | 5618 | 7813 | 9259 |
| 5.1 | 1645 | 2134 | 2615 | 2982 | 3592 | 4636 | 5730 | 7969 | 9444 |

Fuse Voltage Drop Chart - Maxi Fuse

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Yellow | Grey | Green | Blu-Green | Orange | Red | Blue | Tan | Clear |
|-------------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|
| Measurement mV | Maxi 20 Amp | Maxi 25 Amp | Maxi 30 Amp | Maxi 35 Amp | Maxi 40 Amp | Maxi 50 Amp | Maxi 60 Amp | Maxi 70 Amp | Maxi 80 Amp |
| 5.2 | 1677 | 2176 | 2667 | 3041 | 3662 | 4727 | 5843 | 8125 | 9630 |
| 5.3 | 1710 | 2218 | 2718 | 3099 | 3732 | 4818 | 5955 | 8281 | 9815 |
| 5.4 | 1742 | 2259 | 2769 | 3158 | 3803 | 4909 | 6067 | 8438 | 10000 |
| 5.5 | 1774 | 2301 | 2821 | 3216 | 3873 | 5000 | 6180 | 8594 | 10185 |
| 5.6 | 1806 | 2343 | 2872 | 3275 | 3944 | 5091 | 6292 | 8750 | 10370 |
| 5.7 | 1839 | 2385 | 2923 | 3333 | 4014 | 5182 | 6404 | 8906 | 10556 |
| 5.8 | 1871 | 2427 | 2974 | 3392 | 4085 | 5273 | 6517 | 9063 | 10741 |
| 5.9 | 1903 | 2469 | 3026 | 3450 | 4155 | 5364 | 6629 | 9219 | 10926 |
| 6 | 1935 | 2510 | 3077 | 3509 | 4225 | 5455 | 6742 | 9375 | 11111 |
| 6.1 | 1968 | 2552 | 3128 | 3567 | 4296 | 5545 | 6854 | 9531 | 11296 |
| 6.2 | 2000 | 2594 | 3179 | 3626 | 4366 | 5636 | 6966 | 9688 | 11481 |
| 6.3 | 2032 | 2636 | 3231 | 3684 | 4437 | 5727 | 7079 | 9844 | 11667 |
| 6.4 | 2065 | 2678 | 3282 | 3743 | 4507 | 5818 | 7191 | 10000 | 11852 |
| 6.5 | 2097 | 2720 | 3333 | 3801 | 4577 | 5909 | 7303 | 10156 | 12037 |
| 6.6 | 2129 | 2762 | 3385 | 3860 | 4648 | 6000 | 7416 | 10313 | 12222 |
| 6.7 | 2161 | 2803 | 3436 | 3918 | 4718 | 6091 | 7528 | 10469 | 12407 |
| 6.8 | 2194 | 2845 | 3487 | 3977 | 4789 | 6182 | 7640 | 10625 | 12593 |
| 6.9 | 2226 | 2887 | 3538 | 4035 | 4859 | 6273 | 7753 | 10781 | 12778 |
| 7 | 2258 | 2929 | 3590 | 4094 | 4930 | 6364 | 7865 | 10938 | 12963 |
| 7.1 | 2290 | 2971 | 3641 | 4152 | 5000 | 6455 | 7978 | 11094 | 13148 |
| 7.2 | 2323 | 3013 | 3692 | 4211 | 5070 | 6545 | 8090 | 11250 | 13333 |
| 7.3 | 2355 | 3054 | 3744 | 4269 | 5141 | 6636 | 8202 | 11406 | 13519 |
| 7.4 | 2387 | 3096 | 3795 | 4327 | 5211 | 6727 | 8315 | 11563 | 13704 |
| 7.5 | 2419 | 3138 | 3846 | 4386 | 5282 | 6818 | 8427 | 11719 | 13889 |
| 7.6 | 2452 | 3180 | 3897 | 4444 | 5352 | 6909 | 8539 | 11875 | 14074 |
| 7.7 | 2484 | 3222 | 3949 | 4503 | 5423 | 7000 | 8652 | 12031 | 14259 |
| 7.8 | 2516 | 3264 | 4000 | 4561 | 5493 | 7091 | 8764 | 12188 | 14444 |
| 7.9 | 2548 | 3305 | 4051 | 4620 | 5563 | 7182 | 8876 | 12344 | 14630 |
| 8 | 2581 | 3347 | 4103 | 4678 | 5634 | 7273 | 8989 | 12500 | 14815 |
| 8.1 | 2613 | 3389 | 4154 | 4737 | 5704 | 7364 | 9101 | 12656 | 15000 |
| 8.2 | 2645 | 3431 | 4205 | 4795 | 5775 | 7455 | 9213 | 12813 | 15185 |
| 8.3 | 2677 | 3473 | 4256 | 4854 | 5845 | 7545 | 9326 | 12969 | 15370 |
| 8.4 | 2710 | 3515 | 4308 | 4912 | 5915 | 7636 | 9438 | 13125 | 15556 |
| 8.5 | 2742 | 3556 | 4359 | 4971 | 5986 | 7727 | 9551 | 13281 | 15741 |
| 8.6 | 2774 | 3598 | 4410 | 5029 | 6056 | 7818 | 9663 | 13438 | 15926 |
| 8.7 | 2806 | 3640 | 4462 | 5088 | 6127 | 7909 | 9775 | 13594 | 16111 |
| 8.8 | 2839 | 3682 | 4513 | 5146 | 6197 | 8000 | 9888 | 13750 | 16296 |
| 8.9 | 2871 | 3724 | 4564 | 5205 | 6268 | 8091 | 10000 | 13906 | 16481 |
| 9 | 2903 | 3766 | 4615 | 5263 | 6338 | 8182 | 10112 | 14063 | 16667 |
| 9.1 | 2935 | 3808 | 4667 | 5322 | 6408 | 8273 | 10225 | 14219 | 16852 |
| 9.2 | 2968 | 3849 | 4718 | 5380 | 6479 | 8364 | 10337 | 14375 | 17037 |
| 9.3 | 3000 | 3891 | 4769 | 5439 | 6549 | 8455 | 10449 | 14531 | 17222 |
| 9.4 | 3032 | 3933 | 4821 | 5497 | 6620 | 8545 | 10562 | 14688 | 17407 |
| 9.5 | 3065 | 3975 | 4872 | 5556 | 6690 | 8636 | 10674 | 14844 | 17593 |
| 9.6 | 3097 | 4017 | 4923 | 5614 | 6761 | 8727 | 10787 | 15000 | 17778 |
| 9.7 | 3129 | 4059 | 4974 | 5673 | 6831 | 8818 | 10899 | 15156 | 17963 |
| 9.8 | 3161 | 4100 | 5026 | 5731 | 6901 | 8909 | 11011 | 15313 | 18148 |
| 9.9 | 3194 | 4142 | 5077 | 5789 | 6972 | 9000 | 11124 | 15469 | 18333 |
| 10 | 3226 | 4184 | 5128 | 5848 | 7042 | 9091 | 11236 | 15625 | 18519 |

Fuse Voltage Drop Chart - Mini Fuse

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Grey | Violet | Pink | Tan | Brown | Red | Blue | Yellow | Clear | Green |
|-------------------|---------------|---------------|---------------|---------------|-----------------|----------------|----------------|----------------|----------------|----------------|
| Measurement mV | Mini 2 Amp | Mini 3 Amp | Mini 4 Amp | Mini 5 Amp | Mini 7.5 Amp | Mini 10 Amp | Mini 15 Amp | Mini 20 Amp | Mini 25 Amp | Mini 30 Amp |
| 0.1 | 2 | 3 | 4 | 6 | 9 | 13 | 22 | 31 | 42 | 54 |
| 0.2 | 4 | 6 | 9 | 11 | 18 | 27 | 44 | 62 | 85 | 108 |
| 0.3 | 5 | 9 | 13 | 17 | 28 | 40 | 66 | 93 | 127 | 162 |
| 0.4 | 7 | 12 | 17 | 23 | 37 | 54 | 87 | 125 | 169 | 216 |
| 0.5 | 9 | 15 | 21 | 28 | 46 | 67 | 109 | 156 | 212 | 270 |
| 0.6 | 11 | 18 | 26 | 34 | 55 | 81 | 131 | 187 | 254 | 324 |
| 0.7 | 13 | 21 | 30 | 39 | 65 | 94 | 153 | 218 | 297 | 378 |
| 0.8 | 14 | 24 | 34 | 45 | 74 | 108 | 175 | 249 | 339 | 432 |
| 0.9 | 16 | 27 | 38 | 51 | 83 | 121 | 197 | 280 | 381 | 486 |
| 1 | 18 | 30 | 43 | 56 | 92 | 135 | 218 | 312 | 424 | 541 |
| 1.1 | 20 | 33 | 47 | 62 | 101 | 148 | 240 | 343 | 466 | 595 |
| 1.2 | 22 | 36 | 51 | 68 | 111 | 162 | 262 | 374 | 508 | 649 |
| 1.3 | 23 | 39 | 55 | 73 | 120 | 175 | 284 | 405 | 551 | 703 |
| 1.4 | 25 | 41 | 60 | 79 | 129 | 189 | 306 | 436 | 593 | 757 |
| 1.5 | 27 | 44 | 64 | 85 | 138 | 202 | 328 | 467 | 636 | 811 |
| 1.6 | 29 | 47 | 68 | 90 | 147 | 216 | 349 | 498 | 678 | 865 |
| 1.7 | 31 | 50 | 72 | 96 | 157 | 229 | 371 | 530 | 720 | 919 |
| 1.8 | 32 | 53 | 77 | 101 | 166 | 243 | 393 | 561 | 763 | 973 |
| 1.9 | 34 | 56 | 81 | 107 | 175 | 256 | 415 | 592 | 805 | 1027 |
| 2 | 36 | 59 | 85 | 113 | 184 | 270 | 437 | 623 | 847 | 1081 |
| 2.1 | 38 | 62 | 89 | 118 | 194 | 283 | 459 | 654 | 890 | 1135 |
| 2.2 | 40 | 65 | 94 | 124 | 203 | 296 | 480 | 685 | 932 | 1189 |
| 2.3 | 41 | 68 | 98 | 130 | 212 | 310 | 502 | 717 | 975 | 1243 |
| 2.4 | 43 | 71 | 102 | 135 | 221 | 323 | 524 | 748 | 1017 | 1297 |
| 2.5 | 45 | 74 | 106 | 141 | 230 | 337 | 546 | 779 | 1059 | 1351 |
| 2.6 | 47 | 77 | 111 | 146 | 240 | 350 | 568 | 810 | 1102 | 1405 |
| 2.7 | 49 | 80 | 115 | 152 | 249 | 364 | 590 | 841 | 1144 | 1459 |
| 2.8 | 50 | 83 | 119 | 158 | 258 | 377 | 611 | 872 | 1186 | 1514 |
| 2.9 | 52 | 86 | 124 | 163 | 267 | 391 | 633 | 903 | 1229 | 1568 |
| 3 | 54 | 89 | 128 | 169 | 276 | 404 | 655 | 935 | 1271 | 1622 |
| 3.1 | 56 | 92 | 132 | 175 | 286 | 418 | 677 | 966 | 1314 | 1676 |
| 3.2 | 58 | 95 | 136 | 180 | 295 | 431 | 699 | 997 | 1356 | 1730 |
| 3.3 | 59 | 98 | 141 | 186 | 304 | 445 | 721 | 1028 | 1398 | 1784 |
| 3.4 | 61 | 101 | 145 | 192 | 313 | 458 | 742 | 1059 | 1441 | 1838 |
| 3.5 | 63 | 104 | 149 | 197 | 323 | 472 | 764 | 1090 | 1483 | 1892 |
| 3.6 | 65 | 107 | 153 | 203 | 332 | 485 | 786 | 1121 | 1525 | 1946 |
| 3.7 | 67 | 110 | 158 | 208 | 341 | 499 | 808 | 1153 | 1568 | 2000 |
| 3.8 | 68 | 113 | 162 | 214 | 350 | 512 | 830 | 1184 | 1610 | 2054 |
| 3.9 | 70 | 116 | 166 | 220 | 359 | 526 | 852 | 1215 | 1653 | 2108 |
| 4 | 72 | 119 | 170 | 225 | 369 | 539 | 873 | 1246 | 1695 | 2162 |
| 4.1 | 74 | 121 | 175 | 231 | 378 | 553 | 895 | 1277 | 1737 | 2216 |
| 4.2 | 76 | 124 | 179 | 237 | 387 | 566 | 917 | 1308 | 1780 | 2270 |
| 4.3 | 77 | 127 | 183 | 242 | 396 | 580 | 939 | 1340 | 1822 | 2324 |
| 4.4 | 79 | 130 | 187 | 248 | 406 | 593 | 961 | 1371 | 1864 | 2378 |
| 4.5 | 81 | 133 | 192 | 254 | 415 | 606 | 983 | 1402 | 1907 | 2432 |
| 4.6 | 83 | 136 | 196 | 259 | 424 | 620 | 1004 | 1433 | 1949 | 2486 |
| 4.7 | 85 | 139 | 200 | 265 | 433 | 633 | 1026 | 1464 | 1992 | 2541 |
| 4.8 | 86 | 142 | 204 | 270 | 442 | 647 | 1048 | 1495 | 2034 | 2595 |
| 4.9 | 88 | 145 | 209 | 276 | 452 | 660 | 1070 | 1526 | 2076 | 2649 |
| 5 | 90 | 148 | 213 | 282 | 461 | 674 | 1092 | 1558 | 2119 | 2703 |

Fuse Voltage Drop Chart - Mini Fuse

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Grey | Violet | Pink | Tan | Brown | Red | Blue | Yellow | Clear | Green |
|-------------------|---------------|---------------|---------------|---------------|-----------------|----------------|----------------|----------------|----------------|----------------|
| Measurement mV | Mini 2 Amp | Mini 3 Amp | Mini 4 Amp | Mini 5 Amp | Mini 7.5 Amp | Mini 10 Amp | Mini 15 Amp | Mini 20 Amp | Mini 25 Amp | Mini 30 Amp |
| 5.1 | 92 | 151 | 217 | 287 | 470 | 687 | 1114 | 1589 | 2161 | 2757 |
| 5.2 | 94 | 154 | 221 | 293 | 479 | 701 | 1135 | 1620 | 2203 | 2811 |
| 5.3 | 95 | 157 | 226 | 299 | 488 | 714 | 1157 | 1651 | 2246 | 2865 |
| 5.4 | 97 | 160 | 230 | 304 | 498 | 728 | 1179 | 1682 | 2288 | 2919 |
| 5.5 | 99 | 163 | 234 | 310 | 507 | 741 | 1201 | 1713 | 2331 | 2973 |
| 5.6 | 101 | 166 | 239 | 315 | 516 | 755 | 1223 | 1745 | 2373 | 3027 |
| 5.7 | 103 | 169 | 243 | 321 | 525 | 768 | 1245 | 1776 | 2415 | 3081 |
| 5.8 | 104 | 172 | 247 | 327 | 535 | 782 | 1266 | 1807 | 2458 | 3135 |
| 5.9 | 106 | 175 | 251 | 332 | 544 | 795 | 1288 | 1838 | 2500 | 3189 |
| 6 | 108 | 178 | 256 | 338 | 553 | 809 | 1310 | 1869 | 2542 | 3243 |
| 6.1 | 110 | 181 | 260 | 344 | 562 | 822 | 1332 | 1900 | 2585 | 3297 |
| 6.2 | 112 | 184 | 264 | 349 | 571 | 836 | 1354 | 1931 | 2627 | 3351 |
| 6.3 | 113 | 187 | 268 | 355 | 581 | 849 | 1376 | 1963 | 2669 | 3405 |
| 6.4 | 115 | 190 | 273 | 361 | 590 | 863 | 1397 | 1994 | 2712 | 3459 |
| 6.5 | 117 | 193 | 277 | 366 | 599 | 876 | 1419 | 2025 | 2754 | 3514 |
| 6.6 | 119 | 196 | 281 | 372 | 608 | 889 | 1441 | 2056 | 2797 | 3568 |
| 6.7 | 121 | 199 | 285 | 377 | 618 | 903 | 1463 | 2087 | 2839 | 3622 |
| 6.8 | 122 | 201 | 290 | 383 | 627 | 916 | 1485 | 2118 | 2881 | 3676 |
| 6.9 | 124 | 204 | 294 | 389 | 636 | 930 | 1507 | 2150 | 2924 | 3730 |
| 7 | 126 | 207 | 298 | 394 | 645 | 943 | 1528 | 2181 | 2966 | 3784 |
| 7.1 | 128 | 210 | 302 | 400 | 654 | 957 | 1550 | 2212 | 3008 | 3838 |
| 7.2 | 129 | 213 | 307 | 406 | 664 | 970 | 1572 | 2243 | 3051 | 3892 |
| 7.3 | 131 | 216 | 311 | 411 | 673 | 984 | 1594 | 2274 | 3093 | 3946 |
| 7.4 | 133 | 219 | 315 | 417 | 682 | 997 | 1616 | 2305 | 3136 | 4000 |
| 7.5 | 135 | 222 | 319 | 423 | 691 | 1011 | 1638 | 2336 | 3178 | 4054 |
| 7.6 | 137 | 225 | 324 | 428 | 700 | 1024 | 1659 | 2368 | 3220 | 4108 |
| 7.7 | 138 | 228 | 328 | 434 | 710 | 1038 | 1681 | 2399 | 3263 | 4162 |
| 7.8 | 140 | 231 | 332 | 439 | 719 | 1051 | 1703 | 2430 | 3305 | 4216 |
| 7.9 | 142 | 234 | 336 | 445 | 728 | 1065 | 1725 | 2461 | 3347 | 4270 |
| 8 | 144 | 237 | 341 | 451 | 737 | 1078 | 1747 | 2492 | 3390 | 4324 |
| 8.1 | 146 | 240 | 345 | 456 | 747 | 1092 | 1769 | 2523 | 3432 | 4378 |
| 8.2 | 147 | 243 | 349 | 462 | 756 | 1105 | 1790 | 2555 | 3475 | 4432 |
| 8.3 | 149 | 246 | 353 | 468 | 765 | 1119 | 1812 | 2586 | 3517 | 4486 |
| 8.4 | 151 | 249 | 358 | 473 | 774 | 1132 | 1834 | 2617 | 3559 | 4541 |
| 8.5 | 153 | 252 | 362 | 479 | 783 | 1146 | 1856 | 2648 | 3602 | 4595 |
| 8.6 | 155 | 255 | 366 | 485 | 793 | 1159 | 1878 | 2679 | 3644 | 4649 |
| 8.7 | 156 | 258 | 371 | 490 | 802 | 1173 | 1900 | 2710 | 3686 | 4703 |
| 8.8 | 158 | 261 | 375 | 496 | 811 | 1186 | 1921 | 2741 | 3729 | 4757 |
| 8.9 | 160 | 264 | 379 | 501 | 820 | 1199 | 1943 | 2773 | 3771 | 4811 |
| 9 | 162 | 267 | 383 | 507 | 829 | 1213 | 1965 | 2804 | 3814 | 4865 |
| 9.1 | 164 | 270 | 388 | 513 | 839 | 1226 | 1987 | 2835 | 3856 | 4919 |
| 9.2 | 165 | 273 | 392 | 518 | 848 | 1240 | 2009 | 2866 | 3898 | 4973 |
| 9.3 | 167 | 276 | 396 | 524 | 857 | 1253 | 2031 | 2897 | 3941 | 5027 |
| 9.4 | 169 | 279 | 400 | 530 | 866 | 1267 | 2052 | 2928 | 3983 | 5081 |
| 9.5 | 171 | 281 | 405 | 535 | 876 | 1280 | 2074 | 2960 | 4025 | 5135 |
| 9.6 | 173 | 284 | 409 | 541 | 885 | 1294 | 2096 | 2991 | 4068 | 5189 |
| 9.7 | 174 | 287 | 413 | 546 | 894 | 1307 | 2118 | 3022 | 4110 | 5243 |
| 9.8 | 176 | 290 | 417 | 552 | 903 | 1321 | 2140 | 3053 | 4153 | 5297 |
| 9.9 | 178 | 293 | 422 | 558 | 912 | 1334 | 2162 | 3084 | 4195 | 5351 |
| 10 | 180 | 296 | 426 | 563 | 922 | 1348 | 2183 | 3115 | 4237 | 5405 |

Fuse Voltage Drop Chart - Standard Fuse (ATO,ATC)

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Black | Grey | Violet | Pink | Tan | Brown | Red | Blue | Yellow | Clear | Green | Blu-Green | Orange |
|----------------|----------------|----------------|----------------|----------------|----------------|------------------|-----------------|-----------------|-----------------|-----------------|-----------------|-----------------|-----------------|
| Measurement mV | Standard 1 Amp | Standard 2 Amp | Standard 3 Amp | Standard 4 Amp | Standard 5 Amp | Standard 7.5 Amp | Standard 10 Amp | Standard 15 Amp | Standard 20 Amp | Standard 25 Amp | Standard 30 Amp | Standard 35 Amp | Standard 40 Amp |
| 0.1 | 1 | 2 | 3 | 4 | 6 | 9 | 13 | 21 | 30 | 40 | 51 | 62 | 69 |
| 0.2 | 2 | 4 | 6 | 9 | 11 | 18 | 26 | 42 | 59 | 79 | 102 | 124 | 139 |
| 0.3 | 2 | 6 | 10 | 13 | 17 | 27 | 39 | 63 | 89 | 119 | 152 | 186 | 208 |
| 0.4 | 3 | 7 | 13 | 18 | 22 | 37 | 52 | 83 | 118 | 159 | 203 | 248 | 278 |
| 0.5 | 4 | 9 | 16 | 22 | 28 | 46 | 65 | 104 | 148 | 198 | 254 | 311 | 347 |
| 0.6 | 5 | 11 | 19 | 26 | 34 | 55 | 78 | 125 | 178 | 238 | 305 | 373 | 417 |
| 0.7 | 6 | 13 | 23 | 31 | 39 | 64 | 91 | 146 | 207 | 278 | 355 | 435 | 486 |
| 0.8 | 7 | 15 | 26 | 35 | 45 | 73 | 104 | 167 | 237 | 317 | 406 | 497 | 556 |
| 0.9 | 7 | 17 | 29 | 39 | 50 | 82 | 117 | 188 | 266 | 357 | 457 | 559 | 625 |
| 1 | 8 | 19 | 32 | 44 | 56 | 92 | 130 | 208 | 296 | 397 | 508 | 621 | 694 |
| 1.1 | 9 | 21 | 35 | 48 | 62 | 101 | 143 | 229 | 325 | 437 | 558 | 683 | 764 |
| 1.2 | 10 | 22 | 39 | 53 | 67 | 110 | 156 | 250 | 355 | 476 | 609 | 745 | 833 |
| 1.3 | 11 | 24 | 42 | 57 | 73 | 119 | 169 | 271 | 385 | 516 | 660 | 807 | 903 |
| 1.4 | 11 | 26 | 45 | 61 | 78 | 128 | 182 | 292 | 414 | 556 | 711 | 870 | 972 |
| 1.5 | 12 | 28 | 48 | 66 | 84 | 137 | 195 | 313 | 444 | 595 | 761 | 932 | 1042 |
| 1.6 | 13 | 30 | 51 | 70 | 90 | 147 | 208 | 333 | 473 | 635 | 812 | 994 | 1111 |
| 1.7 | 14 | 32 | 55 | 75 | 95 | 156 | 221 | 354 | 503 | 675 | 863 | 1056 | 1181 |
| 1.8 | 15 | 34 | 58 | 79 | 101 | 165 | 234 | 375 | 533 | 714 | 914 | 1118 | 1250 |
| 1.9 | 15 | 36 | 61 | 83 | 106 | 174 | 247 | 396 | 562 | 754 | 964 | 1180 | 1319 |
| 2 | 16 | 37 | 64 | 88 | 112 | 183 | 260 | 417 | 592 | 794 | 1015 | 1242 | 1389 |
| 2.1 | 17 | 39 | 68 | 92 | 118 | 192 | 273 | 438 | 621 | 833 | 1066 | 1304 | 1458 |
| 2.2 | 18 | 41 | 71 | 96 | 123 | 202 | 286 | 458 | 651 | 873 | 1117 | 1366 | 1528 |
| 2.3 | 19 | 43 | 74 | 101 | 129 | 211 | 299 | 479 | 680 | 913 | 1168 | 1429 | 1597 |
| 2.4 | 20 | 45 | 77 | 105 | 134 | 220 | 312 | 500 | 710 | 952 | 1218 | 1491 | 1667 |
| 2.5 | 20 | 47 | 80 | 110 | 140 | 229 | 325 | 521 | 740 | 992 | 1269 | 1553 | 1736 |
| 2.6 | 21 | 49 | 84 | 114 | 146 | 238 | 338 | 542 | 769 | 1032 | 1320 | 1615 | 1806 |
| 2.7 | 22 | 50 | 87 | 118 | 151 | 247 | 351 | 563 | 799 | 1071 | 1371 | 1677 | 1875 |
| 2.8 | 23 | 52 | 90 | 123 | 157 | 257 | 364 | 583 | 828 | 1111 | 1421 | 1739 | 1944 |
| 2.9 | 24 | 54 | 93 | 127 | 162 | 266 | 377 | 604 | 858 | 1151 | 1472 | 1801 | 2014 |
| 3 | 24 | 56 | 96 | 132 | 168 | 275 | 390 | 625 | 888 | 1190 | 1523 | 1863 | 2083 |
| 3.1 | 25 | 58 | 100 | 136 | 174 | 284 | 403 | 646 | 917 | 1230 | 1574 | 1925 | 2153 |
| 3.2 | 26 | 60 | 103 | 140 | 179 | 293 | 416 | 667 | 947 | 1270 | 1624 | 1988 | 2222 |
| 3.3 | 27 | 62 | 106 | 145 | 185 | 302 | 429 | 688 | 976 | 1310 | 1675 | 2050 | 2292 |
| 3.4 | 28 | 64 | 109 | 149 | 190 | 312 | 442 | 708 | 1006 | 1349 | 1726 | 2112 | 2361 |
| 3.5 | 28 | 65 | 113 | 154 | 196 | 321 | 455 | 729 | 1036 | 1389 | 1777 | 2174 | 2431 |
| 3.6 | 29 | 67 | 116 | 158 | 202 | 330 | 468 | 750 | 1065 | 1429 | 1827 | 2236 | 2500 |
| 3.7 | 30 | 69 | 119 | 162 | 207 | 339 | 481 | 771 | 1095 | 1468 | 1878 | 2298 | 2569 |
| 3.8 | 31 | 71 | 122 | 167 | 213 | 348 | 494 | 792 | 1124 | 1508 | 1929 | 2360 | 2639 |
| 3.9 | 32 | 73 | 125 | 171 | 218 | 357 | 506 | 813 | 1154 | 1548 | 1980 | 2422 | 2708 |
| 4 | 33 | 75 | 129 | 175 | 224 | 367 | 519 | 833 | 1183 | 1587 | 2030 | 2484 | 2778 |
| 4.1 | 33 | 77 | 132 | 180 | 230 | 376 | 532 | 854 | 1213 | 1627 | 2081 | 2547 | 2847 |
| 4.2 | 34 | 79 | 135 | 184 | 235 | 385 | 545 | 875 | 1243 | 1667 | 2132 | 2609 | 2917 |
| 4.3 | 35 | 80 | 138 | 189 | 241 | 394 | 558 | 896 | 1272 | 1706 | 2183 | 2671 | 2986 |
| 4.4 | 36 | 82 | 141 | 193 | 246 | 403 | 571 | 917 | 1302 | 1746 | 2234 | 2733 | 3056 |
| 4.5 | 37 | 84 | 145 | 197 | 252 | 412 | 584 | 938 | 1331 | 1786 | 2284 | 2795 | 3125 |
| 4.6 | 37 | 86 | 148 | 202 | 258 | 422 | 597 | 958 | 1361 | 1825 | 2335 | 2857 | 3194 |
| 4.7 | 38 | 88 | 151 | 206 | 263 | 431 | 610 | 979 | 1391 | 1865 | 2386 | 2919 | 3264 |
| 4.8 | 39 | 90 | 154 | 211 | 269 | 440 | 623 | 1000 | 1420 | 1905 | 2437 | 2981 | 3333 |
| 4.9 | 40 | 92 | 158 | 215 | 275 | 449 | 636 | 1021 | 1450 | 1944 | 2487 | 3043 | 3403 |
| 5 | 41 | 93 | 161 | 219 | 280 | 458 | 649 | 1042 | 1479 | 1984 | 2538 | 3106 | 3472 |
| 5.1 | 41 | 95 | 164 | 224 | 286 | 467 | 662 | 1063 | 1509 | 2024 | 2589 | 3168 | 3542 |
| 5.2 | 42 | 97 | 167 | 228 | 291 | 477 | 675 | 1083 | 1538 | 2063 | 2640 | 3230 | 3611 |
| 5.3 | 43 | 99 | 170 | 232 | 297 | 486 | 688 | 1104 | 1568 | 2103 | 2690 | 3292 | 3681 |
| 5.4 | 44 | 101 | 174 | 237 | 303 | 495 | 701 | 1125 | 1598 | 2143 | 2741 | 3354 | 3750 |
| 5.5 | 45 | 103 | 177 | 241 | 308 | 504 | 714 | 1146 | 1627 | 2183 | 2792 | 3416 | 3819 |
| 5.6 | 46 | 105 | 180 | 246 | 314 | 513 | 727 | 1167 | 1657 | 2222 | 2843 | 3478 | 3889 |
| 5.7 | 46 | 107 | 183 | 250 | 319 | 522 | 740 | 1188 | 1686 | 2262 | 2893 | 3540 | 3958 |
| 5.8 | 47 | 108 | 186 | 254 | 325 | 532 | 753 | 1208 | 1716 | 2302 | 2944 | 3602 | 4028 |
| 5.9 | 48 | 110 | 190 | 259 | 331 | 541 | 766 | 1229 | 1746 | 2341 | 2995 | 3665 | 4097 |
| 6 | 49 | 112 | 193 | 263 | 336 | 550 | 779 | 1250 | 1775 | 2381 | 3046 | 3727 | 4167 |
| 6.1 | 50 | 114 | 196 | 268 | 342 | 559 | 792 | 1271 | 1805 | 2421 | 3096 | 3789 | 4236 |
| 6.2 | 50 | 116 | 199 | 272 | 347 | 568 | 805 | 1292 | 1834 | 2460 | 3147 | 3851 | 4306 |
| 6.3 | 51 | 118 | 203 | 276 | 353 | 577 | 818 | 1313 | 1864 | 2500 | 3198 | 3913 | 4375 |
| 6.4 | 52 | 120 | 206 | 281 | 359 | 587 | 831 | 1333 | 1893 | 2540 | 3249 | 3975 | 4444 |

Fuse Voltage Drop Chart - Standard Fuse (ATO,ATC)

Circuit Current Across Fuse (milliAmps)



| Fuse Color | Black | Grey | Violet | Pink | Tan | Brown | Red | Blue | Yellow | Clear | Green | Blu-Green | Orange |
|----------------|----------------|----------------|----------------|----------------|----------------|------------------|-----------------|-----------------|-----------------|-----------------|-----------------|-----------------|-----------------|
| Measurement mV | Standard 1 Amp | Standard 2 Amp | Standard 3 Amp | Standard 4 Amp | Standard 5 Amp | Standard 7.5 Amp | Standard 10 Amp | Standard 15 Amp | Standard 20 Amp | Standard 25 Amp | Standard 30 Amp | Standard 35 Amp | Standard 40 Amp |
| 6.5 | 53 | 121 | 209 | 285 | 364 | 596 | 844 | 1354 | 1923 | 2579 | 3299 | 4037 | 4514 |
| 6.6 | 54 | 123 | 212 | 289 | 370 | 605 | 857 | 1375 | 1953 | 2619 | 3350 | 4099 | 4583 |
| 6.7 | 54 | 125 | 215 | 294 | 375 | 614 | 870 | 1396 | 1982 | 2659 | 3401 | 4161 | 4653 |
| 6.8 | 55 | 127 | 219 | 298 | 381 | 623 | 883 | 1417 | 2012 | 2698 | 3452 | 4224 | 4722 |
| 6.9 | 56 | 129 | 222 | 303 | 387 | 632 | 896 | 1438 | 2041 | 2738 | 3503 | 4286 | 4792 |
| 7 | 57 | 131 | 225 | 307 | 392 | 642 | 909 | 1458 | 2071 | 2778 | 3553 | 4348 | 4861 |
| 7.1 | 58 | 133 | 228 | 311 | 398 | 651 | 922 | 1479 | 2101 | 2817 | 3604 | 4410 | 4931 |
| 7.2 | 59 | 135 | 232 | 316 | 403 | 660 | 935 | 1500 | 2130 | 2857 | 3655 | 4472 | 5000 |
| 7.3 | 59 | 136 | 235 | 320 | 409 | 669 | 948 | 1521 | 2160 | 2897 | 3706 | 4534 | 5069 |
| 7.4 | 60 | 138 | 238 | 325 | 415 | 678 | 961 | 1542 | 2189 | 2937 | 3756 | 4596 | 5139 |
| 7.5 | 61 | 140 | 241 | 329 | 420 | 687 | 974 | 1563 | 2219 | 2976 | 3807 | 4658 | 5208 |
| 7.6 | 62 | 142 | 244 | 333 | 426 | 697 | 987 | 1583 | 2249 | 3016 | 3858 | 4720 | 5278 |
| 7.7 | 63 | 144 | 248 | 338 | 431 | 706 | 1000 | 1604 | 2278 | 3056 | 3909 | 4783 | 5347 |
| 7.8 | 63 | 146 | 251 | 342 | 437 | 715 | 1013 | 1625 | 2308 | 3095 | 3959 | 4845 | 5417 |
| 7.9 | 64 | 148 | 254 | 346 | 443 | 724 | 1026 | 1646 | 2337 | 3135 | 4010 | 4907 | 5486 |
| 8 | 65 | 150 | 257 | 351 | 448 | 733 | 1039 | 1667 | 2367 | 3175 | 4061 | 4969 | 5556 |
| 8.1 | 66 | 151 | 260 | 355 | 454 | 742 | 1052 | 1688 | 2396 | 3214 | 4112 | 5031 | 5625 |
| 8.2 | 67 | 153 | 264 | 360 | 459 | 752 | 1065 | 1708 | 2426 | 3254 | 4162 | 5093 | 5694 |
| 8.3 | 67 | 155 | 267 | 364 | 465 | 761 | 1078 | 1729 | 2456 | 3294 | 4213 | 5155 | 5764 |
| 8.4 | 68 | 157 | 270 | 368 | 471 | 770 | 1091 | 1750 | 2485 | 3333 | 4264 | 5217 | 5833 |
| 8.5 | 69 | 159 | 273 | 373 | 476 | 779 | 1104 | 1771 | 2515 | 3373 | 4315 | 5280 | 5903 |
| 8.6 | 70 | 161 | 277 | 377 | 482 | 788 | 1117 | 1792 | 2544 | 3413 | 4365 | 5342 | 5972 |
| 8.7 | 71 | 163 | 280 | 382 | 487 | 797 | 1130 | 1813 | 2574 | 3452 | 4416 | 5404 | 6042 |
| 8.8 | 72 | 164 | 283 | 386 | 493 | 807 | 1143 | 1833 | 2604 | 3492 | 4467 | 5466 | 6111 |
| 8.9 | 72 | 166 | 286 | 390 | 499 | 816 | 1156 | 1854 | 2633 | 3532 | 4518 | 5528 | 6181 |
| 9 | 73 | 168 | 289 | 395 | 504 | 825 | 1169 | 1875 | 2663 | 3571 | 4569 | 5590 | 6250 |
| 9.1 | 74 | 170 | 293 | 399 | 510 | 834 | 1182 | 1896 | 2692 | 3611 | 4619 | 5652 | 6319 |
| 9.2 | 75 | 172 | 296 | 404 | 515 | 843 | 1195 | 1917 | 2722 | 3651 | 4670 | 5714 | 6389 |
| 9.3 | 76 | 174 | 299 | 408 | 521 | 852 | 1208 | 1938 | 2751 | 3690 | 4721 | 5776 | 6458 |
| 9.4 | 76 | 176 | 302 | 412 | 527 | 862 | 1221 | 1958 | 2781 | 3730 | 4772 | 5839 | 6528 |
| 9.5 | 77 | 178 | 305 | 417 | 532 | 871 | 1234 | 1979 | 2811 | 3770 | 4822 | 5901 | 6597 |
| 9.6 | 78 | 179 | 309 | 421 | 538 | 880 | 1247 | 2000 | 2840 | 3810 | 4873 | 5963 | 6667 |
| 9.7 | 79 | 181 | 312 | 425 | 543 | 889 | 1260 | 2021 | 2870 | 3849 | 4924 | 6025 | 6736 |
| 9.8 | 80 | 183 | 315 | 430 | 549 | 898 | 1273 | 2042 | 2899 | 3889 | 4975 | 6087 | 6806 |
| 9.9 | 80 | 185 | 318 | 434 | 555 | 907 | 1286 | 2063 | 2929 | 3929 | 5025 | 6149 | 6875 |
| 10 | 81 | 187 | 322 | 439 | 560 | 917 | 1299 | 2083 | 2959 | 3968 | 5076 | 6211 | 6944 |